

**DATOS ELECTRICOS MOTORES TRIFASICOS @  
220VAC**

HP	AMPS @ 220VAC	CABLE MINIMO	TERMOMAGNETICO REQUERIDO
1/2 HP	2.2	14 AWG	5 AMPS
3/4 HP	3	14 AWG	5 AMPS
1 HP	4	14 AWG	15 AMPS
1.5 HP	5	14 AWG	15 AMPS
2 HP	7	14 AWG	15 AMPS
3 HP	9	14 AWG	15 AMPS
5 HP	15	12 AWG	20 AMPS
7.5 HP	20	10 AWG	30 AMPS
10 HP	27	8 AWG	40 AMPS
15 HP	44	6 AWG	70 AMPS
20 HP	56	6 AWG	100 AMPS
25 HP	64	6 AWG	100 AMPS
30 HP	70	4 AWG	125 AMPS
40 HP	100	2 AWG	175 AMPS
50 HP	125	1 AWG	200 AMPS
60 HP	152	1/0 AWG	225 AMPS
75 HP	186	3/0 AWG	300 AMPS
100 HP	240	250 MCM	400 AMPS
125 HP	300	350 MCM	500 AMPS
150 HP	360	500 MCM	600 AMPS

**DATOS ELECTRICOS MOTORES TRIFASICOS @  
440VAC**

HP	AMPS @ 440VAC	CABLE MINIMO	TERMOMAGNETICO REQUERIDO
1/2 HP	1.1	14 AWG	5 AMPS
3/4 HP	1.5	14 AWG	5 AMPS
1 HP	2	14 AWG	5 AMPS
1.5 HP	2.7	14 AWG	5 AMPS
2 HP	3.5	12 AWG	15 AMPS
3 HP	4.5	12 AWG	15 AMPS
5 HP	7.5	12 AWG	15 AMPS
7.5 HP	10	12 AWG	15 AMPS
10 HP	13.5	12 AWG	20 AMPS
15 HP	22	10 AWG	30 AMPS
20 HP	28	8 AWG	40 AMPS
25 HP	32	6 AWG	70 AMPS
30 HP	39	6 AWG	70 AMPS
40 HP	50	6 AWG	100 AMPS
50 HP	63	4 AWG	100 AMPS
60 HP	76	2 AWG	125 AMPS
75 HP	93	2 AWG	175 AMPS
100 HP	120	1 AWG	200 AMPS
125 HP	150	1/0 AWG	500 AMPS
150 HP	180	3/0 AWG	300 AMPS
200 HP	240	250MCM	400 AMPS
250 HP	295	350 MCM	500 AMPS
300 HP	300	500 MCM	600 AMPS